

BoonTouch



**BOON EDAM**

Secured entry solutions help you manage the different flows of people through your lobby. Staff can use their badges to pass through the building but for visitors the intervention of a security guard or receptionist is required. The BoonTouch remote control panel allows receptionists and security guards to easily and quickly allow access to different visitors.

Options

- Choice of mounting options
- Retrofittable on current installations
- Language configurable
- Configurable functionality

 *your entry experts*



Intuitive User Interface

The BoonTouch is a remote control panel with a capacitive touch screen that allows the receptionist or security guard to operate the secured entry solutions in the building with a simple touch. During the design process particular attention was given to the user interface. With the help of interface experts and after extensive usability testing, we have created a clear and simple design that can be operated intuitively.

This control panel is able to operate any combination of up to 6 security access solutions and is compatible with most of the solutions in our product range. Its user friendly interface allows for each solution to be operated separately or all at the same time.



Full Control

The BoonTouch gives a security guard or receptionist full control over the bank of secured entry products in their area. Alarm situations show directly on the screen. Each lane can be managed individually or all at once to for example close the entry for the night.

Technical Specifications

BoonTouch

Display:	7" Wide screen LCD
	Capacitive Touch Screen
Resolution:	800 x 480 pixels
Power Supply:	12V DC / 0.83A / 10W
Mains Voltage:	100-240 V AC / 47-63 Hz

CAN I/O adapter

Inputs:	8 inputs 24 V DC
Outputs:	8 outputs (relay dry-contact) 24V / 1A DC or 48V / 500mA

CAN-connection

Can Cable Type:	Twisted pair
Maximum Total Cable Length:	328 feet